



Harrington Signal Inc.
2519 4th Avenue, Moline, Illinois 61265
P.O. Box 590, Moline, Illinois 61266-0590
Phone: (800) 577-5758 Local: (309) 762-0731 Fax: (309) 762-8215
Internet: www.harringtonfire.com



Description

System Sensor 100 Series Plug-In Smoke Detectors offer superb performance and reliability in a profile which is just 1.6" (4.2cm) deep. Model 2151

(photoelectronic sensor) can be used with a variety of different adapter bases in several wiring configurations and voltages. Other features include: low current draw, stable performance in high air velocities, built-in tamper resistant base design, remote LED option, removable cover, and built-in test switch.

The 100 series is designed to meet the performance criteria designated by UL. Its sensing chambers are sealed against back pressure air flow, dirt, and insects. This chamber is protected by a fine mesh screen which can be cleaned or replaced. Additional key features include a variety of mounting bases and a full line of accessories.

Photoelectronic

All 100 Series photoelectronic smoke detectors contain a unique optical sensing chamber designed

to sense smoke particles produced by a wide range of combustion sources. A custom integrated circuit incorporates signal processing to reduce false alarms.

Features

- Sleek, low-profile design
- Compatible with 400 Series Product
- Two LEDs blink in standby, providing 360° visibility
- Field sensitivity metering of detector to meet the requirements of NFPA 72
- Broad range of adapter bases available with built-in shunting spring

Specifications

Operating Voltage / Alarm Current
See Adapter Base Selection Guide following

Standby Current
Photo: 85µA Standby

Sensitivity
3% ± 7%/ft. Photo

Shipping Weight
3.6 oz. (102 g)

Size
1.66" h. (42 mm)
4.1" / 104 mm dia. unflanged base
6.1" / 155 mm dia. flanged base



Construction
Flame Retardant thermoplastic

Temperature
32° to 120°F (0° to 49°C)

UL Listed Velocity Range
Photo: 0 - 3000 fpm (0 - 15.2m/s)

Humidity Range
10% - 93% RH noncondensing

Smoke Detector Spacing
on smooth ceilings (as defined in NFPA 72), spacing of 30 feet (900 sq. ft.) may be used as a guide. Other spacing may be used depending on ceiling height, high air movements, and other conditions or response requirements.

Ordering Information

Model Number	Part Number	Description
2151	2151	Low-profile photoelectric detector. Must be mounted to one of the B100 Series or B400 Series bases listed in Adapter Base Selection Guide



Adapter Base Selection Guide							
Base Model Number	Loop Type	Current Limit Resistor	Contact Type	Nominal Voltage	Current Draw on Alarm (mA)		
B100LP	2-wire*	No	-	12/24VDC	10-130		
B110RLP	2-wire*	Yes	-	24VDC	10-62		
B112LP	4-wire	Yes	Form A&C	24VDC	17-36		
B114LP	4-wire	Yes	Form A&C + A Supervisory	120VAC	75 mA AC Max		
B116LP	2-wire*	No	Form C	24VDC	20-100**		
B401†	2-wire*	No	-	12/24VDC	10-130**		
*Functionality contingent on panel compatibility							
**Must be limited by control panel							
†Flangeless base							
Relay Contact Ratings: Resistive or Inductive (60% power factor) load.							
Form A:	2.0A at 30 VAC/DC						
Form C:	0.6A at 110VDC, 2.0A at 30VDC						
	1.0A at 125VAC, 2.0A at 30VAC						
Junction Box Selection Guide							
Base Model Number	Single Gang	3½ Octagon	4" Octagon	4" Square	50 mm	60mm	75mm
B401	No	No	No	No	Yes	Yes	No
B110LP/RLP	Yes	Yes	Yes	Yes	No	No	No
B112LP/B116LP	Yes	Yes	Yes	Yes	Yes	Yes	Yes
B114LP	No	No	Yes	Yes	No	No	No

NOTICE: The information contained in this document is intended only as a summary and is subject to change without notice. The products described have specific instructional/installation documentation, which covers various technical, approval, code, limitation and liability information. Copies of this documentation along with any general product warning and limitation documents, which also contain important information, are provided with the product and are also available from Harrington Signal Inc. The information contained in all of these documents should be considered before specifying or using the products. Any example applications shown are subject to the most current enforced local/national codes, standards, approvals, certifications, and/or the authority having jurisdiction. All of these resources, as well as the specific manufacturer of any shown or mentioned related equipment, should be consulted prior to any implementation. For further information or assistance concerning the products, contact Harrington Signal Inc. Harrington Signal Inc. reserves the right to change any and all documentation without notice. Quality manufactured for Harrington Signal Inc. Fire Alarm by System Sensor.